

Code: VRX-2

RECEIVER 2.4 GHz **VRX-2** 4 CHANNELS

The VRX-2 receiver allows to receive audio (2 channels) and video (1 channel) signals. For GP-1 antenna the transmission range is about 200 m. For longer distance transmission we have to use the antennas with better gain parameter. The device enables continuous receiving the signals from one transmitter on jumper selected single channel (1, 2, 3 or 4). Inside there are the LED indicators, the green one informs about power supply, the red one indicates signal level - it is helpful for antennas installation settings.

It can be used outdoors, but under a roof. Due to connectors the case boxes are classified as splash-proof.



Frequency range:	2.400 ... 2.4835 GHz
Number of channels:	4
Video signal level:	1 Vpp / 75 Ω
Audio signal level:	1 Vpp / 1.5 kΩ
Receiver sensitivity:	- 80 dB/m
Connectors:	SMA-RP BNC
Impedance:	50 Ω
Power supply:	11 - 14 V 180 mA
Operation temp:	-25 °C ... +70 °C
Dimensions:	90 x 75 x 40 mm
Guarantee:	2 years

