

Code: UD-P3303A

LABORATORY POWER SUPPLY **UD-P3303A** UNI-T

Net: **381.42 EUR** Gross: **469.15 EUR**



The UD-P3303A laboratory power supply allows you to generate a constant voltage or current with strictly defined parameters. The device can work in one of two modes: as a source of constant voltage or as a source of constant current.

Additionally, the power supply adapter has the option of internal serial or parallel connection of outputs.

SPECIFICATION

Output voltage range of the power adapter:	0 ... 30 V
Power supply output current range:	0 ... 3 A
Output power:	195 W
Setting resolution:	<ul style="list-style-type: none">• Voltage : 10 mV• Current : 1 mA
Setting accuracy:	<ul style="list-style-type: none">• Voltage $\leq \pm (0.1\% + 30\text{mV})$• Current $\leq \pm (0.3\% + 5\text{mA})$
Ripple and noise:	<ul style="list-style-type: none">• Voltage : $\leq 1 \text{ mV RMS}$• Current : $\leq 3 \text{ mA RMS}$
Number of outputs:	3 : <ul style="list-style-type: none">• 2x : 0 ... 30 V DC / 0 ... 3 A,• 1x : 1.8 / 2.5 / 3.3 / 5 V DC / 3 A
Display:	EBTN display
Main features:	<ul style="list-style-type: none">• Possibility of serial or parallel connection of outputs• In parallel mode, the maximum current is about 6A• In serial mode the maximum voltage is about 60V• Symmetric mode - in this mode it is possible to obtain a common ground for two power sources, with the maximum voltage of -30V and +30V respectively• USB output for charging / powering devices : 5 V / 2 A
Power supply:	100 / 120 / 220 / 230 V AC - selectable by switch
Operation temp. / Relative humidity:	0 °C ... 40 °C / $\leq 80 \%$
Weight:	8.6 kg
Dimensions:	241 x 170 x 347 mm
Manufacturer / Brand:	UNI-T
Guarantee:	2 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Front view:



Rear view:





In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------