

Code: MT-47

MODULATOR TV MT-47

Net: 38.43 EUR Gross: 38.43 EUR

Double sideband modulator controlled by a microprocessor. The choice of output channel is performed with two buttons (after opening the top cover), and the channel number or any changeable parameter is displayed on the LED display. Channel number and other parameters values are stored in non-volatile memory. Use of quartz-stabilized PLL practically eliminates frequency error. The modulators can be connected in cascade. They also enable combine modulated signals with terrestrial TV signal. There is a possibility to protect the modulator against unauthorized access. Please note, in comparison to the previous series, these Terra modulators can provide compatibility with many versions of the PAL system.



SPECIFICATION

Inputs:	1 pcs Video composite (Cinch) 1 pcs RF (F) 2 pcs audio (Cinch)
Output:	1 pcs RF (F)
Video input frequency range:	20 Hz ... 6 MHz
Video input level / impedance:	1 V \pm 1 dB / 75 Ω
Audio input frequency range:	20 Hz ... 15 kHz
Audio input level adjustment:	1 ... -14 dB
Audio input level / impedance / deviation:	775 mV RMS / 10 k Ω / 50 kHz
Level (typical) / RF output impedance:	85 dB μ V / 75 Ω
RF output level adjustment:	0 ... -20 dB
RF output PAL signal version:	B/G/D/K/H/I/L/M/N/Australia
RF output frequency (channels) range:	170 MHz ... 230 MHz 470 MHz ... 862 MHz (K6-12, K21-69)
Carrier frequency error:	\pm 50 kHz
Audio subcarrier frequency:	4.5 ; 5.5 ; 6.0 ; 6.5 MHz
Fine tuning range of video carrier frequency:	\pm 2.25 MHz max. with 0.25 MHz step
SAT / Terr loop-through loss:	2.5 dB / 1.5 dB
SAT / Terr loop-through frequency range:	47 MHz ... 2150 MHz
Video frequency response:	\pm 1 dB
A/V ratio:	12 / 16 dB
Amplitude modulation depth (typical):	81 %
SNR (weighted):	\geq 55 dB
Power supply:	230 V AC @ 50Hz
Power consumption:	2.5 W

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Operation temp:	-10 °C ... 50 °C
Main features:	<ul style="list-style-type: none"> • video carrier frequency adjustment • audio subcarrier modulation depth changing • audio subcarrier from video carrier frequency distance changing • deviation of audio carrier for input level adjustment
Weight:	0.336 kg
Dimensions:	133 x 73 x 39 mm
Guarantee:	2 years

PRESENTATION

Internal view, after remove the cover:



In the kit:



OUR OPINIONS



- RF loop-through in/out pass full band of RTV/SAT (up to 2150MHz).

PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------