

Code: WS-6934

SATELLITE METER **WS-6934**

Net: **80.22 USD** Gross: **98.67 USD**



The WS-6934 satellite meter allows to quick set the satellite dish signal. The WS-6934 is equipped with readable menu, which helps to operate for each installer. The device has implemented over a dozen satellite positions (satellites + transponders).

The WS-6934 model allows to DVB-S/S2 signals measurement.

Attention! The built-in compass is too inaccurate to correctly determine the direction.

SPECIFICATION

Output and input:	— / F plug
Frequency range:	950 MHz ... 2150 MHz
Signal level:	-65 ... -10 dBm
LNB power supply:	13/18 V, max. 400 mA
Switching between bandwidths:	22 kHz
DiSEqC:	1.0, 1.1, 1.2
Modulation:	QPSK, 8PSK, 16APSK
Symbol rate:	2 ... 45 Msps
SCPC and MCPC support:	✓
Programming and firmware upgrade:	RS232
Battery power supply:	<ul style="list-style-type: none">• Li-Ion battery 1800 mAh• Power adapter 12 V / 1.5 A (power adapter included)
Display:	240 x 320 " TFT LCD
Main features:	<ul style="list-style-type: none">• Sound signaling• Spectrum measurement mode• Signal level is expressed in dBμV, and quality in %• Constellation diagram• Measurement of C/N, S/N, BER• DiSEqC and 22kHz control support• DVB-S signals measurement / DVB-S2 - SD and HD quality channels• Flashlight built-in• UNICABLE 1.0 / 2.0 technology support• Digiturk MDU technology support

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Supported languages:	Polish, English, German
Weight:	0.33 kg
Dimensions:	165 x 85 x 40 mm
Guarantee:	2 years

PRESENTATION

Front panel:



Connectors:





Rear view:



In the kit:

