

Code: DS-7616NXI-I2/4S

IP DVR DS-7616NXI-I2/4S 16 CHANNELS ACUSENSE HikvisionNet: **562.01 EUR** Gross: **691.27 EUR****SPECIFICATION**

| | |
|-------------------------------------|--|
| Standard: | TCP/IP |
| Supported resolutions: | max. 12 Mpx - 4000 x 3000 px |
| Video outputs: | 1 pcs HDMI 1 pcs VGA 1 pcs CVBS There is a possibility to configure a SPOT function on one of the output |
| Audio support: | <ul style="list-style-type: none"> • 16 Channels - Audio from cameras • Bi-directional audio streaming support |
| Audio inputs: | 1 pcs Microphone, CINCH |
| Audio outputs: | 1 pcs CINCH |
| Image compression method: | H.265+ / H.265 / H.264 / H.264+ / MPEG-4 |
| Supported hard drives: | 2 x 8 TB SATA |
| Recording modes: | Manual, Sensor, Motion detection, Schedule |
| Network protocols: | TCP/IP, PPPoE, DHCP, Hik Cloud P2P, DNS, DDNS, NTP, SADP, NFS, iSCSI, UPnP, HTTPS, ONVIF |
| External storage devices backup: | Backup to USB drive (pendrive) |
| Searching and playback the records: | Records searching: by time and events type. Records playback: forward, backward, fast, slow Advanced searching (to the one second accuracy) All channels synchronous playback, Smart Search function Records playback from max. 12 channels in the same time @ 1080p |
| Bitrate: | max. 160 Mbps |
| Network functions: | <ul style="list-style-type: none"> • Live image view, Playback the records, Backup the records • max. 128 on-line users - iVMS-4200 application • ANR - Automatic Network Replenishment allows to save image to the card when the network connection with DVR is break (network failure) and next synchronize its |
| ONVIF: | ✓ |
| Mobile phones support: | Port no.: 8000 or access by a cloud (P2P) Android: Free application iVMS-4500 or Hik-Connect iOS (iPhone): Free application iVMS-4500 or Hik-Connect |
| Default IP address: | 192.168.1.64 |
| Default admin user / password: | admin / - The administrator password should be set at the first start |

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

| | |
|----------------------------------|---|
| Web browser access ports: | 80, 8000 |
| PC client access ports: | 8000 |
| Mobile client access ports: | 8000 |
| RTSP URL: | <ul style="list-style-type: none"> • rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no01/ - Main stream • rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no02/ - Sub stream |
| Alarm inputs / outputs: | 4 / 1 |
| PTZ control: | ✓ |
| Motion Detection: | 22 x 18 motion zones |
| Main features: | <ul style="list-style-type: none"> • NVR from the AcuSense series • Filtering of false alarms based on recognition of persons and vehicles (line crossing, intrusion) - max. 4 Mpx |
| Intelligent Image Analysis: | ✓ |
| Mouse support: | ✓ |
| IR remote controller in the set: | — |
| Power supply: | 12 V DC / 3.33 A (power adapter included) |
| Weight: | 1.83 kg |
| Dimensions: | 380 x 325 x 52 mm |
| Supported languages: | Polish, English, Bulgarian, Croatian, Czech, Danish, Estonian, French, Greek, Spanish, Dutch, Lithuanian, Latvian, German, Norwegian, Portuguese, Russian, Romanian, Serbian, Slovak, Slovenian, Swedish, Turkish, Hungarian, Italian |
| Country of origin: | China |
| Manufacturer / Brand: | Hikvision |
| SAP Code: | 303608347 |
| Guarantee: | 3 years |

PRESENTATION

Front panel:



Rear panel:



See how to mount a hard disk drive and configure the recorder:

:



In the kit:



OUR OPINIONS



- Audio transmission via network.
- The DS-7616NXI-I2/4S is equipped with USB 3.0 port allowing to fast records backup.

