

Code: MD-06B7

## CEILING PIR DETECTOR **MD-06B7** AC 230V

Net: **14.63 EUR** Gross: **17.99 EUR**

Passive Infra Red detector to ceiling mount. The detector is intended for automatic control of switching on of the lighting outside a building (or other electrical devices) after detection of motion nearby its installation site. The core of the device is the passive infrared sensor with the motion detection angle amounting to about 360 degrees. The motion is detected via measurement of the ambient temperature change within the set sensor's visibility sector, as a consequence of motion of the person who is present there.

When motion is detected by the PIR sensor, the lighting automatically turns on (or other electrical device controlled by the sensor) and stays on as long as the motion sensor detects the presence (movement) within the field of view. If no presence is detected within specific time (set by the user), the lighting (or other electrical device) is switched off automatically.

The sensor is additionally equipped with a special photo-optical sensor which, as an option, allows the energy to be saved without switching on the lighting e.g. during the day.



### SPECIFICATION

Sensor type:	Passive Infra Red (PIR)
Detection angle:	360 °
Range:	22 m (max)
Application:	For indoor use - Surface
Sensitivity adjustment:	3 ... 2000 Lux (manual adjustment)
Recommended installation height:	2.2 ... 6 m (ceiling-mounted)
Alarm time:	10 s ... 30 minutes (manual adjustment)
Maximal outputs load:	2000 W (resistance load) 1000 W (inductive load)
Pet immunity:	—
Power supply:	220 V ... 240 V AC @ 50Hz
Color:	White
Operation temp:	-18 ... 40 °C
Safety class:	IP20
Weight:	0.140 kg
Dimensions:	102 x 101 x 59 mm
Manufacturer / Brand:	EURA
Guarantee:	2 years

### PRESENTATION

Bottom view:

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60



View after remove the cover:



Mounting side view:



In the kit:

