

Code: F-3001R

## POWER GENERATOR **F-3001R** 2500 W FOGO

A power generator with manual start is perfect for emergency power supply: a central heating furnace, home, office, camping, industrial equipment, as well as on boats and yachts.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

The generator is equipped with an Automatic Voltage Regulation system AVR, which allows to eliminate unfavorable voltage fluctuations to a large extent.



Nominal power:	2500 W
Output voltage:	230 V AC
Number of outlets:	2 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	AVR
12V DC output:	—
Engine power:	5.6 HP
Engine capacity:	212 cm <sup>3</sup>
Engine type:	Rato R210 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	96 dB
Average fuel consumption:	1.4 l/h
Fuel tank capacity:	3.6 l
Fuel gauge:	✓
Weight:	36.5 kg
Dimensions:	580 x 395 x 405 mm



# DATA SHEET

---

Manufacturer / Brand:	FOGO
Guarantee:	12 months

