

Code: TR-3000

## WIRELESS TRANSMISSION KIT 5.8 GHz **TR-3000** TXRX SET

The kit allows to wireless transmission of audio, video and s-video signals at return remote control.



Frequency range:	5.790 ... 5.866 GHz The channels list Ch 1 = 5.790 GHz Ch 2 = 5.828 GHz Ch 3 = 5.847 GHz Ch 4 = 5.866 GHz
Number of channels:	4
IR transmitter:	max. 10 dBm / 433.92 MHz
Transmitter power:	13 dBm
Transmission range:	max. 60 m (open area)
Modulation:	FM
Video signal level:	1 Vpp / 75 $\Omega$
Audio signal level:	1 Vpp / 75 $\Omega$
IR carrier frequency:	38 kHz / 56 kHz
Receiver sensitivity:	-80 dB/m
Weight:	0.18 kg
Power supply:	12 V / 250 mA (power adapter included)
Proper operation conditions:	<ul style="list-style-type: none"> <li>the kit (transmitter and receiver) supporting the same camera, has to be set to the same channel (switch set to the same number)</li> <li>at the same location, each of used kits has to be set to different channel</li> <li>the transmitter and receiver antennas should be visible to each other (no obstacles like building, walls, trees, etc. between them)</li> </ul> When the antennas are not visible to each other, the transmission range is lower
Dimensions:	111 x 108 x 40 mm
Guarantee:	2 years