

Code: LR1002

## ETHERNET + EPOE CONVERTER **LR1002** DAHUA

The LR1002 device is designed to work as a type of converter from RJ45 to BNC port, which supports data and power supply (ePoE) transmission via coaxial cable. To create a transmission path are required two devices. The LR1002 converter can also work with the LR1002-1ET, LR1002-1EC extenders.



In package:	2 pcs The price for package
LAN ports:	1 pcs RJ45
Transmission ports:	1 pcs BNC
Transmission speed:	10 / 100 Mbps Full Duplex
Transmission range:	max. 1000 m @ 10 Mbps max. 400 m @ 100 Mbps The range of data transfer and power supply is strongly dependent on the cable used and the power required to supply the receiver
Protections:	Overvoltage
Main features:	<ul style="list-style-type: none"> <li>• Plug &amp; Play</li> <li>• MDI/MDI-X auto detection feature - auto detecting the data transmission mode</li> <li>• Support for IP cameras and network devices</li> <li>• Easy installation - doesn't require any configuration of IP nor MAC address</li> <li>• 2 pcs included</li> </ul>
Power supply:	ePoE
Weight:	0.030 kg
Dimensions:	<ul style="list-style-type: none"> <li>• 56 x 27 x 21 mm</li> <li>• 7 cm (cable length)</li> </ul>
Manufacturer / Brand:	DAHUA
Guarantee:	3 years