

Code: ARA-104

## ANTENNA AMPLIFIER **ARA-104** 8 / 12 dB

The ARA-104 is used to TV signal distribution in home antennas installations. Two-stage, low noise, distribution amplifier, allows to connect 4 TV sets to the antenna installation or cable network. Amplifier can be powered directly from included power adapter or via output with using a separator.



Frequency range:	87 MHz ... 774 MHz
Number of inputs/outputs:	1 / 4
Input/output impedance:	75 Ω
Connectors type:	"F"
Gain :	8 / 12 dB
Gain adjustment:	—
S/N ratio:	≤ 4 dB
Maximum output level:	98 dBμV
IMA3 60dB:	92 dBμV
IMA2 60dB:	79 dBμV
Return loss:	≥ 10 dB
Pre-amplifiers powering:	—
Operation temp:	-25 °C ... 55 °C
Power supply:	12 V DC / 65 mA
Weight:	0.1 kg
Dimensions:	112 x 64 x 29 mm



# DATA SHEET

---

Manufacturer / Brand:	AMS
Guarantee:	2 years

