

Code: NVR4116HS-4KS2/L

## IP DVR **NVR4116HS-4KS2/L** 16 CHANNELS DAHUA



|                                     |  |
|-------------------------------------|--|
| Standard:                           | TCP/IP   |
| Supported resolutions:              | max. 8.3 Mpx - 3840 x 2160 px, 4K UHD  |
| Video outputs:                      | 1 pcs HDMI 4K<br>1 pcs VGA   |
| Audio support:                      | 16 Channels - Audio from cameras   |
| Audio inputs:                       | 1 pcs CINCH  |
| Audio outputs:                      | 1 pcs CINCH  |
| Image compression method:           | H.265+ / H.265 / H.264+ / H.264 / MJPEG  |
| Supported hard drives:              | 1 x 10 TB SATA   |
| Recording modes:                    | Manual, Motion Detection, Schedule   |
| Network protocols:                  | HTTP, HTTPS, TCP/IP, IPv4/IPv6, UPnP, SNMP, RTSP, UDP, SMTP, NTP, DHCP, DNS, DDNS, FTP, Alarm Server, IP Search, P2P, ONVIF  |
| External storage devices backup:    | Backup to USB drive (pendrive, external drive)   |
| Searching and playback the records: | Records searching: by time and events type. Records playback: forward, backward, fast, slow<br>1/4/8/9 channel synchronous playback  |
| Bitrate:                            | max. 80 Mbps   |
| Network functions:                  | Full support via network, Remote records copying, Web Server built-in  |
| ONVIF:                              | ✓  |
| Mobile phones support:              | Port no.: 37777 or access by a cloud (P2P)<br><ul style="list-style-type: none"> <li>• Android: Free application <a href="#">DMSS</a></li> <li>• iOS (iPhone): Free application <a href="#">DMSS</a></li> </ul> <p>See how to configure the P2P function in Dahua recorders and how to enable the mobile application</p> |



# DATA SHEET

|                                  |   |
|----------------------------------|---|
| Default admin user / password:   | admin / -<br>The administrator password should be set at the first start  |
| Default IP address:              | 192.168.1.108   |
| Web browser access ports:        | 80, 37777   |
| PC client access ports:          | 37777   |
| Mobile client access ports:      | 37777   |
| RTSP URL:                        | rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=0 - Main stream<br>rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=1 - Sub stream |
| Alarm inputs / outputs:          | —   |
| PTZ control:                     | IP Speed Dome Cameras   |
| Motion Detection:                | ✓   |
| Intelligent Image Analysis:      | ✓   |
| USB:                             | 2 pcs USB 2.0   |
| Mouse support:                   | ✓   |
| IR remote controller in the set: | —   |
| Power supply:                    | 12 V DC / 2 A (power adapter included)  |
| Weight:                          | 0.83 kg   |
| Dimensions:                      | 260 x 225 x 48 mm   |
| Supported languages:             | Polish, English   |
| Manufacturer / Brand:            | DAHUA   |
| Guarantee:                       | <b>3 years</b>  |

