

Code: F-3001/IS

INVERTER POWER GENERATOR **F-3001/IS** 2300 W FOGO

The use of technology with the use of an inverter allows to obtain a stable output voltage that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, camper-vans, boats, etc.

Device in the Silent version - very quiet generator operation at 89 dBA.



Nominal power:	2300 W
Maximum power:	2500 W
Output voltage:	230 V AC
Number of outlets:	1 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	✓
Engine capacity:	122 cm ³
Engine type:	Rato R 120-Vi 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	89 dBA



DATA SHEET

Average fuel consumption:	<ul style="list-style-type: none">• 0.9 l/h - 50 % power• 1.5 l/h - 100 % power
Fuel tank capacity:	4.5 l
Fuel gauge:	✓
Main features:	<ul style="list-style-type: none">• Low oil level indicator light• Overload signaling• Overload protection• Battery charging possible• Save fuel by automatically reducing the revs as the load decreases• Possibility to combine two F-3001/IS power generators into one generator set
Color:	Red
Weight:	24 kg
Dimensions:	520 x 320 x 460 mm
Manufacturer / Brand:	FOGO
Guarantee:	12 months