

Code: FH-6001TR

## POWER GENERATOR **FH-6001TR** 5600 W Honda GX 390 FOGO

Power Generator with manual start used as a power source in the event of power failure in the network or as a substitute power source on a construction site, plot, at home or in a workshop. The Honda engine used in the generator ensures high reliability and high work efficiency.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.

The generator is equipped with an Automatic Voltage Regulation system AVR, which allows to eliminate unfavorable voltage fluctuations to a large extent.

The 45-liter fuel tank allows for long periods of uninterrupted operation.



Nominal power:	5600 W
Output voltage:	230 V AC
Number of outlets:	<ul style="list-style-type: none"> <li>• 1 pcs - single-phase 32 A (max),</li> <li>• 1 pcs - single-phase 16 A (max)</li> </ul>
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	AVR
12V DC output:	—
Engine capacity:	389 cm <sup>3</sup>
Engine type:	Honda GX 390 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	96 dB
Average fuel consumption:	2.7 l/h
Fuel tank capacity:	45 l
Fuel gauge:	✓



## DATA SHEET

Main features:	<ul style="list-style-type: none"><li>• Working time with a full fuel tank : 16.7 h - 75 % power,</li><li>• Low oil level indicator light,</li><li>• Silencer with exhaust gas hose connection</li></ul>
Color:	White + Black
Weight:	86 kg
Dimensions:	790 x 600 x 653 mm
Manufacturer / Brand:	FOGO
Guarantee:	<b>3 years</b> - The condition is to conduct paid service every year - a warranty inspection at authorized Honda or FOGO service stations, otherwise 12 months