

Code: DEE1010B-S2

## RELAY MODULE **DEE1010B-S2** DAHUA

The DEE1010B-S2 module allows the expansion of video doorphone features for control of another door or gate. Communication with the device takes place via the RS-485 interface. Built-in relay output allows to control any NO / NC device. The output is switched by video doorphone or mobile phone (DMSS application).



Support:	<ul style="list-style-type: none"> <li>• Cooperation with the DAHUA access control systems,</li> <li>• Designed for DAHUA video doorphones</li> </ul>
Number of relay outputs:	1 x
Outputs:	<ul style="list-style-type: none"> <li>• 1 x NO / NC,</li> <li>• 1 x Exit button,</li> <li>• 1 x Reed switch ,</li> <li>• 2 x RS-485</li> </ul>
Interface:	RS-485, Twisted-pair cable - pair of wires
Main features:	<ul style="list-style-type: none"> <li>• Door contact and request button for exit inputs</li> <li>• Relay to control for example: electric strike or electromagnetic lock</li> </ul>
Operation state indication:	3 x Operation status LED indicator
Power supply:	12 V DC / 1 A
Power consumption:	<ul style="list-style-type: none"> <li>≤ 0.9 W (Standby mode)</li> <li>≤ 1.0 W (operation)</li> </ul>
Operation temp:	-10 °C ... 60 °C
Permissible relative humidity:	0 % ... 95 %
Weight:	0.09 kg



# DATA SHEET

---

Dimensions:	59 x 50 x 21 mm
Manufacturer / Brand:	DAHUA
Guarantee:	2 years

