

Code: BCS-NVR0802-4K-P-III

NVR **BCS-NVR0802-4K-P-III** 8 CHANNELS, 8 PoE BCS Line



Standard:	TCP/IP
Supported resolutions:	max. 12 Mpx - 4000 x 3000 px
Video outputs:	1 pcs HDMI 4K 1 pcs VGA
Audio support:	8 Channels - Audio from cameras
Audio inputs:	1 pcs CINCH
Audio outputs:	1 pcs CINCH
Image compression method:	H.265 / H.265+ / H.264 / H.264+ / MJPEG
Supported hard drives:	2 x 10 TB SATA III Possibility of operation the disks in RAID 1 array
Recording modes:	Manual, Sensor, Motion detection, Schedule
Serial ports:	RS-232, RS-485
Network protocols:	HTTP, HTTPS, TCP/IP, IPv4/IPv6, UPnP, SNMP, RTSP, UDP, SMTP, NTP, DHCP, DNS, IP Filter, PPPoE, DDNS, FTP, Alarm Server, IP Search
External storage devices backup:	Backup to USB drive (pendrive, external drive)
Searching and playback the records:	Records searching: by time and events type. Records playback: forward, backward, fast, slow Advanced searching (to the one second accuracy) All channels synchronous playback, Smart Search function
Bitrate:	max. 320 Mbps
Network functions:	Full support via network, Remote records copying, Web Server built-in max. 128 on-line users
ONVIF:	2.4
Mobile phones support:	Port no.: 37777 or access by a cloud (P2P) • Android: Free application BCS Manager • iOS (iPhone): Free application BCS Manager



DATA SHEET

Default IP address:	192.168.1.108
Default admin user / password:	admin / - The administrator password should be set at the first start
Web browser access ports:	80, 37777
PC client access ports:	37777
Mobile client access ports:	37777
RTSP URL:	rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=0 - Main stream rtsp://admin:haslo@192.168.1.108:554/cam/realmonitor?channel=1&subtype=1 - Sub stream
Alarm inputs / outputs:	4 pcs / 2 pcs - Relay output
PTZ control:	RS-485 - Many protocols
Motion Detection:	22 x 18 motion zones
USB:	1 pcs USB 3.0 1 pcs USB 2.0
Main features:	<ul style="list-style-type: none">• Fisheye-Dewarping - correction of the "fish eye" view to the perspective view• Cooperation with POS (Point of Sale) terminals• ANR - Automatic Network Replenishment allows to save image to the card when the network connection with DVR is break (network failure) and next synchronize its
Mouse support:	✓
IR remote controller in the set:	✓
Switch PoE:	8-port PoE Switch built-in, 25.5 W / Channel, PoE (802.3af/at), max. 130 W (total)
Power supply:	100 ... 240 V AC @ 50 / 60 Hz
Power consumption:	max. 14.5 W (without HDD)
Operation temp:	-10 °C ... 55 °C
Weight:	2.77 kg
Dimensions:	375 x 327 x 53 mm, RACK 19", 1U
Supported languages:	English, Polish
Manufacturer / Brand:	BCS Line
Guarantee:	3 years