

Code: LR1002-1ET-V3

## EXTENDER ETHERNET+PoE **LR1002-1ET-V3** TRANSMITTER DAHUA

The LR1002-1ET-V3 extender allows to increase a distance of transmission of the data and PoE 802.3 at/af, ePoE powering via coaxial cable.

The device operates from the camera side.

**WARNING!** The PoE power is supplied together with data on pairs 1, 2 and 3, 6.



LAN ports:	1 pcs RJ45
Transmission ports:	1 pcs BNC
Transmission speed:	10 / 100 Mbps
Transmission range:	max. 1000 m @ 10 Mbps max. 400 m @ 100 Mbps The range of data transfer and power supply is strongly dependent on the cable used and the power required to supply the receiver
Protections:	Overvoltage
Main features:	<ul style="list-style-type: none"> <li>• Plug &amp; Play</li> <li>• MDI/MDI-X auto detection feature - auto detecting the data transmission mode</li> <li>• Support for IP cameras and network devices</li> <li>• Easy installation - doesn't require any configuration of IP nor MAC address</li> <li>• Power supply PoE - pins 1, 2 and 3, 6</li> <li>• The device operates from the camera side</li> <li>• Possibility to mount on a wall, or on the DIN TS-35 rail</li> <li>• UTP cable length to the camera max. 2 m</li> </ul>
Power supply:	<ul style="list-style-type: none"> <li>• ePoE</li> <li>• PoE (802.3af/at)</li> </ul>
Weight:	0.07 kg
Dimensions:	79 x 64 x 23 mm
Manufacturer / Brand:	DAHUA
Guarantee:	<b>3 years</b>