

Code: SP-IR03

WIRE REMOTE CONTROL REPEATER **SP-IR03** Spacetronik

Wire repeater of the remote controllers for audio-video components allows to control even several devices, which are located behind closed doors or hidden, for example inside equipment closet.

The IR signal receiver must be fixed in the designated place. IR signal transmitter should be glued in such a way that it covers the "window" for receiving the signal from the remote control on the device.



Number of signal receivers from remote controllers:	1 pcs
Number of emitters:	2 pcs
Length of the cable:	<ul style="list-style-type: none"> • 2 m - IR receiver / USB • 2 m - IR receiver / Jack socket • 3 m - IR transmitters / Jack plug
IR receiver operation frequency range:	20 ... 60 kHz
Main features:	<ul style="list-style-type: none"> • Supports max. 2 devices • LED indication - IR receiver • Plug & Play • Can be mounted on any flat surface with double-sided adhesive tape attached at the back
Power supply:	5 V DC - from USB port
Weight:	0.066 kg (total)
Dimensions:	<ul style="list-style-type: none"> • 30 x 17 x 13 mm - Receiver • 13 x 8 x 5 mm - Transmitter
Manufacturer / Brand:	Spacetronik
Guarantee:	2 years

