

Code: SW-2/1-DSQ-SIG

## SWITCH **SW-2/1-DSQ-SIG** DiSEqC 2.0 SIGNAL

Switch allows to receive by satellite receiver the channels from 2 satellite positions (e.g. Astra and Hot Bird). The switch is controlled via DiSEqC signal in version 2.0. Switch operates with most of currently manufactured digital satellite receivers equipped with DiSEqC generator.

The switch can be installed indoors and outdoors.



SAT frequency range:	950 MHz ... 2150 MHz
Attenuation:	2 dB
Isolation between inputs:	25 dB
Passing voltage:	12 ... 20 V DC
DiSEqC:	2.0
Number of inputs:	2 pcs
Number of outputs:	1 pcs
Connectors type:	F type connectors
Main features:	<ul style="list-style-type: none"> <li>• load 500 mA</li> <li>• High separation of inputs and outputs</li> <li>• Grounding connector</li> <li>• Housing - Plastic (ABS)</li> <li>• Easy and universal mounting system</li> <li>• Cable ties - 2 pcs included</li> </ul>
Weight:	0.06 kg
Dimensions:	80 x 79 x 30 mm
Manufacturer / Brand:	SIGNAL
Guarantee:	2 years