

Code: AQUA-LUNA

## PIR DETECTOR **AQUA-LUNA** SATEL

Digital passive PIR detector with remotely controlled built-in LED emergency lighting. To control the detector LED lighting is used the output of the alarm control panel preprogrammed as desired.



Application:	Indoor
Pyroelectric sensor:	Double
Sensor type:	Passive Infra Red (PIR)
Range:	15 x 14 m
Sensitivity adjustment:	3-step
Prealarm feature:	✓
Alarm time:	2 s
Maximal outputs load:	40 mA / 16 V DC
Digital temperature compensation:	✓
Pet immunity:	—
Power supply:	12 V DC / 12 mA
Operation temp:	-10 °C ... 55 °C
Target speed range:	0.3 ... 3 m/s



# DATA SHEET

Main features:	<ul style="list-style-type: none"><li>• Remote control of the LED emergency lighting</li><li>• Max. current consumption by LED lighting 28 mA</li></ul>
Weight:	0.072 kg
Dimensions:	63 x 96 x 49 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years