

Code: DINB-13830

BUFFERED SWITCHING POWER SUPPLY ADAPTER **DINB-13830**

The buffered power supply adapter is designed to powering control panels, sensors, code locks, cameras, consoles, intercoms and other alarm system equipment. DINB-13830 is designed to mount on the DIN 35 mm rail.



| | |
|------------------------------|--|
| Adapter type: | Switching |
| Input voltage: | 90 ... 264 V AC |
| Output voltage: | <ul style="list-style-type: none"> • 11 ... 13.8 V DC (buffer operation) • 9 ... 13.8 V DC (battery mode) |
| Max. output current (total): | 3.5 A |
| Battery charging current: | 0.5 A |
| Power: | 48 W (max) |
| Protections: | <ul style="list-style-type: none"> • Short-circuit • Overvoltage • Overload • Reverse polarity connection • Discharge |
| Adapter operation control: | <ul style="list-style-type: none"> • AC input voltage presence indication • DC output voltage presence indication • Battery charging indication |
| Housing type: | Plastic, DIN, TS-35 rail mounting |
| Weight: | 0.36 kg |
| Dimensions: | 122 x 93 x 50 mm |
| Manufacturer / Brand: | PULSAR |



DATA SHEET

| | |
|------------|---------|
| Guarantee: | 2 years |
|------------|---------|