

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order. If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity;
2. Improper results of operation of the product or products related with it;
3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.

The IDS-7204HUHI-M1/S/A digital recorder with AHD (Analog High Definition), HD-CVI (High Definition Composite Video Interface), HD-TVI (High Definition Transport Video Interface), TCP/IP and CVBS interface is a professional device applicable in surveillance systems. The recorder supports AcuSense technology, allowing to filter false alarms based on the recognition of people and vehicles.

The menu options layout has been designed for all users, even beginners can easy navigate and change parameters in DVR settings without any problem.





User Manual

Code: IDS-7204HUHI-M1/S/A

AHD, HD-CVI, HD-TVI, CVBS, IP DVR **IDS-7204HUHI-M1/S/A** 4 CHANNELS Hikvision

Standard:	AHD, HD-CVI, HD-TVI, CVBS, TCP/IP
Video inputs:	4 pcs BNC - AHD / HD-CVI / HD-TVI / CVBS
Video outputs:	1 pcs HDMI 1 pcs VGA 1 pcs CVBS - BNC socket
Audio inputs:	4 pcs CINCH, Coaxial audio - Audio from cameras
Audio outputs:	1 pcs CINCH
Image compression method:	H.265+ / H.265 / H.264 / H.264+
Image records resolutions:	<ul style="list-style-type: none">• HD-TVI : 8 Mpx - 3840 x 2160 1 CH only , 8M-N - 1920 x 2160 2,3,4 CH only , 5 Mpx - 2560 x 1944 , 3.7 Mpx - 2560 x 1440 , 3 Mpx - 1920 x 1536 , 1080p - 1920 x 1080 , 720p - 1280 x 720 ,• AHD : 5 Mpx - 2560 x 1944 , 3.7 Mpx - 2560 x 1440 , 1080p - 1920 x 1080 , 720p - 1280 x 720 ,• HD-CVI : 3.7 Mpx - 2560 x 1440 , 1080p - 1920 x 1080 , 720p - 1280 x 720 ,• PAL : 960H - 960 x 576 ,• IP : max. 8 Mpx - 3840 x 2160
Recording speed adjustment:	8 Mpx IP @ 1 ... 25 fps 8 Mpx @ 1 ... 8 fps 8M-N @ 1 ... 15 fps 5 Mpx @ 1 ... 12 fps 4 Mpx @ 1 ... 15 fps 3 Mpx @ 1 ... 18 fps 1080p @ 1 ... 25 fps 720p @ 1 ... 25 fps 960H @ 1 ... 25 fps for each channel
Operation modes:	4 x HD-TVI / AHD / HD-CVI / CVBS / IP + 4 x IP
Recording modes:	Manual, Sensor, Motion detection, Schedule
Supported hard drives:	1 x 10 TB SATA
External storage devices backup:	Backup to USB drive (pendrive, external drive)
Searching and playback the records:	Records searching: timeline or file list. Playback: forward, fast, slow. Playback max. 4 cameras in the same time
Network interface:	1 x RJ-45 - 10/100 Base-TX
Bitrate:	32 ... 10240 kbps



User Manual

Code: IDS-7204HUHI-M1/S/A

AHD, HD-CVI, HD-TVI, CVBS, IP DVR **IDS-7204HUHI-M1/S/A** 4 CHANNELS Hikvision

Network functions:	Network Client Software and IE browser: live view, playback and backup of the records, partial configuration of the recorder parameters
Network protocols:	TCP/IP, PPPoE, DHCP, Hik-Connect, DNS, DDNS, NTP, SADP, NFS, iSCSI, UPnP, HTTPS, ONVIF
Mobile phones support:	Port no.: 8000 or access by a cloud (P2P) Android: iVMS-4500 free application or Hik-Connect iOS (iPhone): iVMS-4500 free application or Hik-Connect
Default IP address:	DHCP or 192.168.1.64
Default admin user / password:	admin / - The administrator password should be set at the first start
Web browser access ports:	80
PC client access ports:	554 RTSP, 8000
Mobile client access ports:	8000
Port ONVIF:	80
RTSP URL:	<ul style="list-style-type: none">• rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no01/ - Main stream• rtsp://user:password@192.168.1.64:554/Streaming/Channels/channel_no02/ - Sub stream
Alarm inputs / outputs:	4 / 1
PTZ control:	<ul style="list-style-type: none">• Control compatible with coax HD-TVI Hikvision• RS-485 - PELCO-D/P
Motion Detection:	Split the screen into zones : 22 x 18 motion zones
USB:	2 x USB 2.0
Mouse support:	✓
IR remote controller in the set:	✓
Main features:	<ul style="list-style-type: none">• DVR from the AcuSense series• Intelligent Image Analysis : crossing the line (tripwire), intrusion, Deep Learning technology• Smart motion detection (with recognizing people and vehicles)• Filtering of false alarms based on the recognition of persons and vehicles
Power supply:	12 V DC / 1.5 A (power adapter included)
Color:	Black
Weight:	1.19 kg
Dimensions:	315 x 250 x 45 mm
Supported languages:	Polish, English, Bulgarian, Croatian, Czech, Danish, Estonian, Greek, Spanish, Dutch, German, Norwegian, Portuguese, Russian, Romanian, Serbian, Slovak, Slovenian, Swedish, Turkish, Hungarian, Italian
Manufacturer / Brand:	Hikvision
SAP Code:	300224953
Guarantee:	3 years

Front panel

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



Rear view



See how to mount a hard disk drive and configure the recorder

In the kit



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------

