

Warning!

Please read the user manual included in this work as it contains important information related with safety of installation and use of the device.

Only persons who read the user manual may use the device.

The user manual must be kept because it may be required in the future. The device is to be used exclusively for purposes specified in this user manual.

The device must be unpacked prior to starting-up. After removing the packaging make sure the device is in working order. If the product has defects, it should not be used until it is repaired.

The product is intended for use at home and commercial use and may not be used for other than intended use.

The manufacturer is not liable for damages resulting from not adhering to the rules contained in the user manual, therefore, we recommend to follow the aforementioned safety rules for operation and maintenance of the device. In this way you will ensure yourself safety and avoid causing damage to the device.

The manufacturer and the supplier are not liable for losses or damages arising out of the product, including financial or intangible losses, loss of profits, income, data, pleasure from use of the product or other products related with it - indirect, incidental or consequential loss or damage. The above provisions apply whether the loss or damage concerns:

1. Deterioration of quality or the lack of operation of the products or products related with it due to damage as well as the lack of access to the product when it is undergoing repair, which results in stoppage the loss of user's time or a break in business activity; 2. Improper results of operation of the product or products related with it;

3. It applies to losses and damages according to any legal category, including negligence and other losses, termination of a contract, expressed or implied guarantee and strict liability (even if the manufacturer or the supplier was notified about the possibility of occurrence of such damages).

Safety measures:

Particular attention at designing was directed to quality standards of the device where ensuring safety of operation is the most important factor.

The device must be secured against contact with caustic, staining and viscous fluids.

The device was designed in such a way that it restarts operation when power supply is restored after a break.

Attention! We recommend using protections to further protect the device from possible overvoltages in installations. Surge protectors are effective protection against accidental pass to the device voltages higher than the rated. Damages caused by pass the voltages higher than specified in manual, are not under warranty.

Turn off the device before transporting it.

Prior to connecting the device to a power source check whether the supplied voltage is consistent with rated voltage specified in the user manual.

Proper product disposal:

A marking of a crossed out waste bin indicates that the product may not be disposed together with other household waste in the entire EU. To avoid possible damage to the natural environment of health due to uncontrolled waste disposal, therefore, it should be handed over for recycling, propagating in this way sustainable use of natural resources.

To return a worn-out product, use a collection and disposal system of this type of equipment or contact a seller from whom it was purchased. He will then be recycled in an environmentally-friendly way.





User Manual

Code: DS-2CD2H46G2-IZS(2.8-12MM) IP VANDALPROOF CAMERA DS-2CD2H46G2-IZS(2.8-12MM) ACUSENSE - 5 Mpx - MOTOZOOM

Hikvision



IP camera with efficient H.265 / H.264 image compression algorithm for clear and smooth video streaming at maximal resolution of 5 Mpx. Due to above it is perfect solution for surveillance systems requiring persons or vehicles recognition.

The camera uses a motozoom lens with a focal length of 2.8 ... 12 mm. The range of IR illumination according to the manufacturer data, depends on outer conditions (visibility - air transparency, environment, wall colors ie. scene reflectance). PoE powering possibility, compatible with the 802.3af standard makes the device more universal and easier to install.

Camera is according to IP66 Index of Protection norm. This is a camera from the Darkfighter series, designed for work in difficult lighting conditions.

Standard:	TCP/IP
Sensor:	1/2.7 " Progressive Scan CMOS
Matrix size:	5 Mpx
Resolution:	2592 x 1944 - 5 Mpx , 2688 x 1520 - 4 Mpx , 2304 x 1296 - 3 Mpx , 1920 x 1080 - 1080p , 1280 x 720 - 720p
Lens:	2.8 12 mm - Motozoom
View angle:	 108 ° 33 ° (manufacturer data) 100 ° 30 ° (our tests result)
Range of IR illumination:	40 m
RS-485 interface:	-
Memory card slot:	Micro SD memory cards up to 256GB support (possible local recording)
Image compression method:	H.265+ / H.265 / H.264+ / H.264 / MJPEG
Alarm inputs / outputs:	1/1
Audio:	 1 Input 1 Output Bi-directional audio streaming support
Network interface:	10/100 Base-T (RJ-45)





Network protocols:	TCP/IP, ICMP, HTTP, HTTPS, FTP, DHCP, DNS, DDNS, RTP, RTSP, NTP, UPnP, SMTP, IGMP, IEEE 802.1x, QoS, IPv4/IPv6, UDP, Bonjour, SSL / TLS, PPPoE, SNMP
WEB Server:	Built-in
Max. number of on-line users:	6
ONVIF:	18.12
Mobile phones support:	Port no.: 8000 or access by a cloud (P2P) • Android: Free application <u>iVMS-4500</u> or <u>Hik-Connect</u> • iOS (iPhone): Free application <u>iVMS-4500</u> or <u>Hik-Connect</u>
Default admin user / password:	admin / - The administrator password should be set at the first start
Default IP address:	192.168.1.64
Web browser access ports:	80
PC client access ports:	Port no.: 8000 or access by a cloud (P2P) - iVMS-4200 application
Mobile client access ports:	8000
Port ONVIF:	80
RTSP URL:	Main stream rtsp://user:password@192.168.1.64:554/Streaming/Channels/101/ - with authorization Sub stream rtsp://user:password@192.168.1.64:554/Streaming/Channels/102/ - with authorization
Main stream frame rate:	20 fps @ 5 Mpx 25 fps @ 4 Mpx
Main features:	 Camera from AcuSense series WDR - 120 dB - Wide Dynamic Range 3D-DNR - Digital Noise Reduction ROI - improve the quality of selected parts of image Anti-Flicker - The technology eliminates the tiring eyes flickering image effect ANR - Automatic Network Replenishment allows to save image to the card when the network connection with DVR is break (network failure) and next synchronize its EXIR - high-efficiency infrared LEDs technology, which evenly covers the whole plan of both central vantage points of the scene as well as the corners BLC/HLC - Back Light / High Light Compensation Day/Night mode (color/b&w/auto) ICR - Movable InfraRed filter WB - White Balance AGC - Automatic Gain Control Mirror - Mirror image Configurable: brightness, contrast, saturation Sharpness - sharper image outlines Configurable Privacy Zones Motion Detection Filtering of false alarms based on the recognition of persons and vehicles Intelligent Image Analysis : intrusion, crossing the line (tripwire), entering the marked area, leaving the marked area, scene changing, face detection, advanced face capture features
Power supply:	• PoE (802.3af), • 12 V DC / 920 mA
Power consumption:	• ≤ 12.5 W @ PoE (802.3af) • ≤ 11 W @ 12 V DC
Housing:	Dome - Metal
Color:	White





"Index of Protection":	IP66
Vandal-proof:	IK10
Operation temp:	-30 °C 60 °C
Weight:	1.14 kg
Dimensions:	Ø 136 x 146 mm
Supported languages:	Polish, English, Bulgarian, Croatian, Czech, Danish, Estonian, Finnish, French, Greek, Spanish, Dutch, Lithuanian, Latvian, German, Norwegian, Portuguese, Russian, Romanian, Serbian, Slovak, Slovenian, Swedish, Turkish, Ukrainian, Hungarian, Italian
Manufacturer / Brand:	Hikvision
SAP Code:	311313730
Guarantee:	3 years

Camera is out from clamping ring:



Memory card slot and "Reset" button:









Camera connectors:







Mounting side view:











Dimensions:





In the kit:







PACKAGE

Dimensions (L x W x H): 0x0x0 mm Gross Weight: 0 kg

