

Code: SINUS-2000/24

## CONVERTER MODULE **SINUS-2000/24**

Net: 686.40 PLN Gross: 686.40 PLN

Inverter module increasing the voltage.

Due to the ideal sine wave approximation (the same as in the power grid), the SINUS-2000/24 is ideal for powering inductive and capacitive devices, such as: power tools, low-power household appliances, heaters, central heating pumps, etc.



### SPECIFICATION

Type:	Increasing the voltage, DC/AC
Power voltage:	21 V ... 31 V DC
Input current:	max. 100 A
Output voltage:	225 V ... 235 V AC
Output voltage adjustment:	—
Power:	<ul style="list-style-type: none"><li>• 2000 W (max),</li><li>• 1000 W (continuous operation)</li></ul>
Efficiency:	> 92 % (at full load)
Length of the cables:	0.9 m
Protections:	<ul style="list-style-type: none"><li>• Short-circuit</li><li>• Overload</li><li>• Overheat</li></ul>
Weight:	2.3 kg
Dimensions:	320 x 135 x 75 mm
Guarantee:	2 years

### PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



Connectors:



Mounting dimensions:



In the kit:



## OUR OPINIONS



- The SINUS-2000/24 is perfect for powering all kind of devices, both inductive and capacitive ones.

## PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------