


Code: INT-PP/IT

EXPANDER **INT-PP/IT** 8 INPUTS/8 OUTPUTS SATEL

Net: **882.37 PLN** Gross: **882.37 PLN**

The device allows to extend the control panel with 8 additional inputs operating the NO, NC, EOL, 2EOL/NO, 2EOL/NC, 3EOL configurations as well as 8 programmable relay outputs and OC outputs.

This device is dedicated for INTEGRA alarm control panels.




SPECIFICATION


Number of inputs:	8 pcs - programmable
Number of outputs:	8 pcs - programmable
Tamper output:	✓
Support configurations:	NO, NC, EOL, 2EOL/NO, 2EOL/NC, 3EOL
Load capacity of OC type programmable outputs:	50 mA / 12 V DC
Relay contacts rating (resistive load):	2 A / 24 V DC
Current-carrying capacity of +12V output:	2.5 A / 12 V DC
Power supply:	12 V DC
Current consumption at standby mode:	35 mA
Maximal current consumption:	150 mA
RS-485 interface:	Remote update of module software
Protection class (Grade):	3
Environmental class EN 50130-5:	II
Operation temp:	-10 °C ... 55 °C
Weight:	0.08 kg
Dimensions:	140 x 69 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years

PRESENTATION

Top view:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------