

Code: MD-16B7

PIR DETECTOR **MD-16B7** AC 230V FOR LIGHTING CONTROL EL HOME

Net: **47.06 PLN** Gross: **47.06 PLN**

The MD-16B7 motion detector is designed to control lighting or other electrical devices supplied with 230V AC inside and outside buildings. When motion is detected in the detector's field of view, power is supplied to the receiver for the time specified by the built-in time delay setting. In addition, the device is equipped with a light intensity sensor and a regulator of the highest light intensity, at which the detector will work.

The maximum load of the relay used in the detector is 1200W for a resistive load or 500W for an inductive load.



SPECIFICATION

Sensor type:	Passive Infra Red (PIR)
Detection angle:	220 °
Range:	12 m
Application:	For outdoor use
Sensitivity adjustment:	3 ... 2000 Lux (manual adjustment)
Recommended installation height:	1.8 ... 2.5 m over the floor (wall-mounted)
Adjusting the time of switching on the lighting:	10 s ... 15 minutes
Maximal outputs load:	1200 W (resistance load) 500 W (inductive load)
Pet immunity:	—
Power supply:	220 V ... 240 V AC @ 50Hz
"Index of Protection":	IP44
Color:	Black
Weight:	0.16 kg
Dimensions:	115 x 80 x 66 mm
Operation temp:	-20 °C ... 40 °C
Manufacturer / Brand:	EL HOME
Guarantee:	2 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Bottom view (adjusting potentiometers visible):



Mounting side view:



View after removing the cover from the mounting side:





In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60