




	<a href="#">POWER DISTRIBUTION UNIT OR-AE-13144 (4 OUTLETS + 2 USB) ORNO</a>	<a href="#">INVERTER POWER GENERATOR F-2001/IS 1800 W FOGO</a>
		
	72.68 PLN 72.68 PLN	2803.08 PLN 2803.08 PLN
Nominal power	...	1800 W
Maximum power	...	2000 W
Rated voltage	230 V AC / 50 Hz	...
Output voltage	...	230 V AC
Total maximal current	10 A	...
Maximal total load	2300 W	...
Built-in voltmeter	...	—
Number of outlets	<ul style="list-style-type: none"> <li>• 4 grounded outlets 10A/250V,</li> <li>• 2 USB ports 2.1A/5V</li> </ul>	1 pcs - single-phase
Output frequency	...	50 Hz
Switch	—	...
Voltage stabilization	...	Inverter (provides full voltage stabilization)
Length of the cable	1.4 m	...
12V DC output	...	✓
Housing	Plastic	...
Engine capacity	...	79.7 cm <sup>3</sup>
Engine type	...	Rato R 80 I 1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine	...	Manual
Noise level during operation	...	89 dB
Average fuel consumption	...	<ul style="list-style-type: none"> <li>• 0.67 l/h - 50 % power</li> <li>• 1.1 l/h - 100 % power</li> </ul>
Fuel tank capacity	...	4 l
Fuel gauge	...	✓
Main features	...	<ul style="list-style-type: none"> <li>• Low oil level indicator light</li> <li>• Overload signaling</li> <li>• Overload protection</li> <li>• Battery charging possible</li> <li>• Save fuel by automatically reducing the revs as the load decreases</li> <li>• Possibility to combine two F-2001/IS power generators into one generator set</li> </ul>
Color	White + Gray	Red

Weight	0.35 kg	21.1 kg
Dimensions	94 x 78 x 78 mm	498 x 290 x 459 mm
Manufacturer / Brand	ORNO	FOGO
Guarantee	2 years	12 months



DELTA-OPTI Monika Matysiak / VAT:PL5251295225 / 60-713 Poznań, ul. Graniczna 10  
Tel:+48 61 864 69 60 / GSM:+48 607 60 11 66 / Fax:+48 61 864 69 65 / e-mail: info@delta.poznan.pl  
Monday-Friday: 8.00-19.00 / Saturday: 8.00-14.00