

Code: LR2226-24ET-360

Switch PoE **LR2226-24ET-360** 26-PORT + 2 x SFP DAHUA

Net: **2 773.00 PLN** Gross: **3 410.79 PLN**

Due to reliability and ensuring high quality of transmission, the LR2226-24ET-360 10/100/1000M 26-port PoE desktop type switch is perfect solution for expanding home or office network.

Attention! The SFP port requires the SFP module, which is available in our offer.

The device is equipped with ePoE technology which enables transmission up to 800 m at a speed of 10 Mb/s or 300 m at a speed of 100 Mb/s via cat. 5e twisted-pair.



SPECIFICATION

Standards:	IEEE 802.3, IEEE 802.3u, IEEE 802.3ab, IEEE 802.3az, IEEE 802.3z, IEEE 802.3af, IEEE 802.3at
Protocols:	CSMA/CD
Management via WWW / console:	<input type="checkbox"/>
LAN ports:	<ul style="list-style-type: none">• 2 x port Combo: SFP (100/1000 Base-X) / RJ45 (10/100/1000 Base-T) - Uplink• 2 x RJ45 10/100 Base-T + Hi-PoE / PoE (802.3af/at) / ePoE• 6 x RJ45 10/100 Base-T + PoE (802.3af/at) / ePoE• 16 x RJ45 10/100 Base-T + PoE (802.3af/at)
Transmission speed:	<ul style="list-style-type: none">• Ethernet - 10 Mb/s Full Duplex• Fast Ethernet - 100 Mb/s Full Duplex• Gigabit Ethernet - 1000 Mb/s Full Duplex (Uplink)
Maximal output power:	<ul style="list-style-type: none">• 30 W / port PoE• 60 W / port Hi-PoE
Maximal total power:	360 W
Transmission method:	Store and Forward
MAC addresses table:	4k
Main features:	<ul style="list-style-type: none">• Switch is web managed• Auto update of MAC addresses table
Default IP address:	192.168.1.110 / 24
Default admin user / password:	admin / - The administrator password should be set at the first start
LED diodes:	Power : 50 % / 80 % / 100 %, Link/Act, PoE, System
Certificates:	FCC Class B, CE
Power supply:	100 ... 240 V AC
Housing type:	RACK 19", 1U
Weight:	3.39 kg
Dimensions:	440 x 300 x 44 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Front panel:



Mounting side view:



In the kit:

