

Code: SINUS-2000

CONVERTER MODULE **SINUS-2000**

Net: **126.82 EUR** Gross: **155.99 EUR**

Inverter module increasing the voltage. The SINUS-2000 device converts the input voltage to the 230V AC value.

Due to the ideal sine wave approximation (the same as in the grid), the SINUS-2000 is ideal for powering inductive and capacitive devices, such as: power tools, low-power household appliances, heaters, central heating pumps, etc.



SPECIFICATION

Type:	Increasing the voltage, DC/AC
Power voltage:	10.5 V ... 15.5 V DC
Input current:	max. 123 A
Output voltage:	<ul style="list-style-type: none">• 225 V ... 235 V AC,• 5 V DC - USB socket
Output voltage adjustment:	<input type="checkbox"/>
Power:	<ul style="list-style-type: none">• 2000 W (instantaneous operation),• 1000 W (continuous operation)
Efficiency:	> 92 % (at full load)
Protections:	<ul style="list-style-type: none">• Short-circuit• Overload• Overvoltage• Overheat
Weight:	2.24 kg
Dimensions:	335 x 135 x 76 mm
Guarantee:	2 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Connectors:




Top view:



Mounting dimensions:



In the kit:



OUR OPINIONS



- The SINUS-2000 is perfect for powering all kind of devices, both inductive and capacitive ones.

