

Code: KW-I3500

# INVERTER POWER GENERATOR **KW-I3500** 3000 VA KraftWele

Net: **624.95 EUR** Gross: **768.69 EUR**

The use of technology with the use of an inverter allows to obtain electricity of a quality that allows for safe powering of electronic receivers.

The inverter generator is used for emergency power supply, e.g. computers, server rooms, telephones, central heating furnace controllers, digitally controlled household equipment, heat pumps, electrically opened gates and garage gates, various medical devices and other devices sensitive to voltage fluctuations. It is also a convenient power supply in the field of tourism, e.g. caravans, camper-vans, boats, etc.

Device in the Silent version - very quiet generator operation at 72 dBA.



## SPECIFICATION

Nominal power:	3000 VA
Maximum power:	3500 VA
Output voltage:	230 V AC
Number of outlets:	2 pcs - single-phase
Built-in voltmeter:	—
Output frequency:	50 Hz
Voltage stabilization:	Inverter (provides full voltage stabilization)
12V DC output:	✓
Engine power:	4 kW
Engine type:	4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	72 dB
Average fuel consumption:	0.7 l/h
Fuel tank capacity:	5.7 l
Fuel gauge:	—
Material:	Plastic + Metal
Color:	Red

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60

Weight:	29.7 kg
Dimensions:	570 x 320 x 480 mm
Manufacturer / Brand:	KraftWele
Guarantee:	2 years

**PRESENTATION**



Front panel:



Side view:



Rear view:



Fuel filler:



Both the weight and size of the device make its transport very easy:



Example of application:



In the kit:

