

Code: DY-2600-B

POWER GENERATOR **DY-2600-B** 2600 W Dynamo

Net: **201.26 EUR** Gross: **201.26 EUR**

A power generator with manual start is perfect for emergency power supply: a central heating furnace, home, office, camping, industrial equipment, as well as on boats and yachts.

The genset engine's rubber stabilizers and engine mounts dampen vibrations and minimize noise.



SPECIFICATION

Nominal power:	2600 W
Maximum power:	3000 W
Output voltage:	230 V AC
Number of outlets:	• 3 pcs - single-phase, • 1 pcs - three-phase - Only one phase available
Built-in voltmeter:	✓
Output frequency:	50 Hz
Voltage stabilization:	AVR
12V DC output:	✓
Alternator windings:	Aluminum
Engine power:	7 HP
Engine capacity:	210 cm ³
Engine type:	1 cylinder, 4 stroke, gasoline, air cooled
Starting the engine:	Manual
Noise level during operation:	92 dB
Fuel tank capacity:	15 l
Fuel gauge:	✓
Color:	Red + Black
Weight:	36.6 kg
Dimensions:	565 x 430 x 430 mm
Manufacturer / Brand:	Dynamo

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Guarantee:

12 months

PRESENTATION



Front panel:



Oil filler:





Muffler:





Spark plug access:





Throttle:



Fuel valve:



The engine is started manually with a recoil starter:



Air filter:



Fuel filler:



Fuel gauge:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------