

Code: DIW-01

SMART LIGHTING DIMMER **DIW-01** Wi-Fi, 230 V AC ZAMEL

Net: **54.41 EUR** Gross: **54.41 EUR**

Smart Wi-Fi dimmer DIW-01 allows you to control the brightness of incandescent lighting, halogen lighting and 230V AC dimmable LED lamps. Control is possible using a physical switch, a web browser, an external BleBox µWiFi controller or the wBox mobile application. The device can also operate as a simple switch for lighting without the possibility of adjusting the lighting power.

To work with full functionality, the device requires connection to a home Wi-Fi network. Control is possible via a physical switch, a web browser, or the SUPLA mobile application.

Beyond direct control, the device has the ability to program the on and off schedule and linking to different system events. Voice control allows you to control the device via voice commands from Amazon Alexa or the Google Assistant (Internet access required).



SPECIFICATION

Support:	SUPLA
Application:	lighting brightness control
Rated voltage:	230 V AC
Maximal total load:	• 150 W (resistance load), • 100 W (inductive or capacitive load - e.g. LED lamp)
Total maximal current:	1.5 A
Number of inputs:	1
Number of outputs:	1
Connector type:	screw terminals
Wireless:	Wi-Fi, 2.4 GHz - IEEE 802.11 b/g/n
Mobile phones support:	• The SUPLA free application on Android • The SUPLA free application on iOS
Main features:	• Local control by physical button, • schedule, • timer, • remote access, • voice control, • Possibility to manually program scenarios from the built-in API, • Wall mounting
Housing:	Plastic
"Index of Protection":	IP20

Color:	Green
Operation temp:	-10 °C ... 55 °C
Weight:	0.04 kg
Dimensions:	47 x 47 x 23 mm
Manufacturer / Brand:	ZAMEL
Guarantee:	2 years

PRESENTATION



Connectors:





PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------