

Code: KONW/OCTO-INVERTO

TV-SAT LNB KONW/OCTO-INVERTO

Net: 46.67 EUR Gross: 46.67 EUR

The Octo LNB is the simplest solution enabling independent operation of 8 receivers using the signals from one satellite.
From receiver side this LNB is visible as standard single LNB with generator frequency 9,75/10,6 GHz.



SPECIFICATION

Type:	OCTO
Input frequency:	<ul style="list-style-type: none">• 10.7 GHz ... 11.7 GHz• 11.7 GHz ... 12.75 GHz
Output frequency:	<ul style="list-style-type: none">• 950 - 1950 MHz• 1100 - 2150 MHz
Oscillator frequency:	9.75 GHz / 10.6 GHz
S/N ratio:	0.2 dB
Number of outputs:	8 pcs F socket
Output impedance:	75 Ω
LNB switch:	—
Gain :	55 dB
H/V polarization switching:	13 / 18 V
Band switching:	22 kHz
Recommended dish diameter:	75 - 90 cm
Neck diameter:	40 mm
Manufacturer / Brand:	INVERTO
Weight:	0.31 kg
Dimensions:	133 x 116 x 65 mm
Guarantee:	2 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------