

Code: KONW/QUAD-INVERTO

TV-SAT LNB **KONW/QUAD-INVERTO**

Net: **66.30 PLN** Gross: **81.55 PLN**

The Quad LNB is the simplest solution enabling independent operation of 4 receivers using the signals from one satellite. From receiver side this LNB is visible as standard single LNB.



SPECIFICATION

| | |
|-----------------------------|--|
| Type: | Quad |
| Input frequency: | <ul style="list-style-type: none">• 10.7 GHz ... 11.7 GHz• 11.7 GHz ... 12.75 GHz |
| Output frequency: | <ul style="list-style-type: none">• 950 - 1950 MHz• 1100 - 2150 MHz |
| Oscillator frequency: | 9.75 GHz / 10.6 GHz |
| S/N ratio: | 0.3 dB |
| Number of outputs: | 4 pcs F socket |
| Output impedance: | 75 Ω |
| LNB switch: | — |
| Gain : | 55 dB |
| H/V polarization switching: | 13 / 18 V |
| Band switching: | 22 kHz |
| Recommended dish diameter: | 80 - 90 cm |
| Neck diameter: | 40 mm |
| Manufacturer / Brand: | INVERTO |
| Weight: | 0.21 kg |
| Dimensions: | 144 x 90 x 68 mm |
| Guarantee: | 2 years |

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60





DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60