

Code: KONW/QUAD-INVERTO

TV-SAT LNB **KONW/QUAD-INVERTO**

Net: **16.61 EUR** Gross: **20.43 EUR**

The Quad LNB is the simplest solution enabling independent operation of 4 receivers using the signals from one satellite. From receiver side this LNB is visible as standard single LNB.



SPECIFICATION

Type:	Quad
Input frequency:	<ul style="list-style-type: none">• 10.7 GHz ... 11.7 GHz• 11.7 GHz ... 12.75 GHz
Output frequency:	<ul style="list-style-type: none">• 950 - 1950 MHz• 1100 - 2150 MHz
Oscillator frequency:	9.75 GHz / 10.6 GHz
S/N ratio:	0.3 dB
Number of outputs:	4 pcs F socket
Output impedance:	75 Ω
LNB switch:	—
Gain :	55 dB
H/V polarization switching:	13 / 18 V
Band switching:	22 kHz
Recommended dish diameter:	80 - 90 cm
Neck diameter:	40 mm
Manufacturer / Brand:	INVERTO
Weight:	0.21 kg
Dimensions:	144 x 90 x 68 mm
Guarantee:	2 years

PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60





DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60