

Code: ZA-106AMS

MULTIPLEXER ZA-106AMS AMS

Net: 9.78 EUR Gross: 9.78 EUR

The ZA-106AMS antenna multiplexer with 2 inputs is used as an element combining signals from 2 antennas (receiving signals in FM (87...110 MHz), and VHF+UHF (174...694 MHz) bands), it is installed on the mast carrying the antenna set.

It is equipped with additional filter to limit the UHF band above 700 MHz.

ZA-106AMS allows to send DC power max. 24V/250mA to power the amplifier mounted in the antenna box (power supply is possible in the VHF/UHF path).



SPECIFICATION

Input:	<ul style="list-style-type: none">• FM : 87 ... 110 MHz - F socket,• VHF/UHF : 174 ... 694 MHz + DC - F socket
Impedance:	75 Ω
Insertion loss:	1 dB
Return loss:	≥ 40 dB
DC-transition:	max. 24 V / 250 mA
Main features:	Built-in >700 MHz filter
Housing:	Metal - Shielded + Plastic
Mount:	To the mast
Weight:	0.09 kg
Dimensions:	90 x 54 x 34 mm
Guarantee:	3 years
Manufacturer / Brand:	AMS

PRESENTATION

Device connectors:

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60



Top view:



Mounting side view:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------

