

Code: LR1002-1ET

EXTENDER ETHERNET+PoE **LR1002-1ET** TRANSMITTER DAHUA

Net: **49.01 EUR** Gross: **60.28 EUR**

The LR1002-1ET extender allows to increase a distance of transmission of the data and PoE 802.3 at/af, ePoE powering via coaxial cable.
The device operates from the camera side.



SPECIFICATION

LAN ports:	1 pcs RJ45
Transmission ports:	1 pcs BNC
Transmission speed:	10 / 100 Mbps Full Duplex
Transmission range:	max. 1000 m @ 10 Mbps max. 400 m @ 100 Mbps The range of data transfer and power supply is strongly dependent on the cable used and the power required to supply the receiver
Protections:	Overvoltage
Main features:	<ul style="list-style-type: none">• Plug & Play• MDI/MDI-X auto detection feature - auto detecting the data transmission mode• Support for IP cameras and network devices• Easy installation - doesn't require any configuration of IP nor MAC address• The device operates from the camera side• Possibility to mount on a wall, or on the DIN TS-35 rail• UTP cable length to the camera max. 2 m
Power supply:	<ul style="list-style-type: none">• ePoE• PoE (802.3af/at)
Weight:	0.061 kg
Dimensions:	79 x 64 x 23 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years

PRESENTATION

Particular elements:



Device connectors:




Rear view:





Transmission schematic diagram:



1. ePoE Switch
2. Coaxial cable
3. UTP cat. 5e
4. Camera IP ePoE
5. Switch PoE
6. Camera IP PoE

In the kit:

