

Code: PPK-8

VIDEO AND AUDIO SWITCH **PPK-8**

Net: **45.64 EUR** Gross: **56.14 EUR**

Switch allows to select one of the several signal sources and switch it to the output. The selection can be manual or automatic. The switching time can be set for all cameras together or for each camera separately. It is also possible to select inputs to bypass them in the sequence.



SPECIFICATION

Standard:	<ul style="list-style-type: none">• AHD - 4 Mpx,• HD-CVI - 1080p,• HD-TVI - 5 Mpx,• CVBS - PAL, NTSC
Video inputs:	8 pcs BNC
Video outputs:	2 pcs BNC
Audio inputs:	8 pcs CINCH
Audio outputs:	2 pcs CINCH
Input impedance:	75 Ω / 10 k Ω
Output impedance:	75 Ω / 39 Ω
PTZ control:	Control keys
Time adjustment range:	0.5 ... 125 s
Power supply:	12 V / 100 mA (power adapter not included)
Assembly:	To the wall
Weight:	0.25 kg
Dimensions:	216 x 100 x 36 mm
Manufacturer / Brand:	DELTA
Guarantee:	3 years

PRESENTATION

Front panel view:



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Rear view:



Rear panel view:

