

Code: BCS-DVR-KN-II

IP / RS-485 KEYBOARD CONTROLLER **BCS-DVR-KN-II**

Net: **427.78 EUR** Gross: **427.78 EUR**

Network keyboard with full possibilities of controlling and programming the PTZ camera heads of the BCS-SD series. It is also possible to control many DVRs from one keyboard.



SPECIFICATION

Protocols:	Pelco-D, Pelco-P, DH-SD, PELCO-D1, PELCO-P1, BCS-DVR - DH1/DH2
Cameras numbers (ID):	1 ... 255
Maximal control distance:	1200 m @ RS-485 / RS-232
Communication standard:	• Ethernet - RJ45 • RS-485 - terminals • RS-232 - terminals
Manipulator:	3-axis joystick, Speed proportional to the swing (possibility of zoom control by joystick)
Display:	LCD - with light indication
PTZ control:	• RS-485 interface - BCS or other manufacturers Speed Dome cameras • RJ-45 socket - BCS only
Power supply:	12 V DC / 0.42 A
Operation temp. / Relative humidity:	-10 °C ... 55 °C / max. 90 % non-condensing
Weight:	0.67 kg
Dimensions:	330 x 160 x 110 mm
Manufacturer / Brand:	BCS
Guarantee:	3 years

PRESENTATION

Top view:



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>
POL; 60-713 Poznań; Graniczna 10
e-mail: delta-opti@delta.poznan.pl; tel: +(48) 61 864 69 60

Keyboard connectors:



In the kit:



PACKAGE

Dimensions (L x W x H): 0x0x0 mm	Gross Weight: 0 kg
----------------------------------	--------------------