

Code: ARA-103

## ANTENNA AMPLIFIER **ARA-103** 11 / 14 dB

Net: **13.93 EUR** Gross: **17.13 EUR**

The ARA-103 is used to TV signal distribution in home antennas installations. Two-stage, low noise, distribution amplifier, allows to connect 3 TV sets to the antenna installation or cable network. Amplifier can be powered directly from included power adapter or via output with using a separator.



### SPECIFICATION

Frequency range:	87 MHz ... 774 MHz
Number of inputs/outputs:	1 / 3
Input/output impedance:	75 $\Omega$
Connectors type:	"F"
Gain :	11 / 14 dB
Gain adjustment:	—
S/N ratio:	$\leq 4$ dB
Maximum output level:	100 dB $\mu$ V
IMA3 60dB:	94 dB $\mu$ V
IMA2 60dB:	81 dB $\mu$ V
Return loss:	$\geq 10$ dB
Pre-amplifiers powering:	—
Operation temp:	-25 °C ... 55 °C
Power supply:	12 V DC / 65 mA
Weight:	0.091 kg
Dimensions:	112 x 64 x 29 mm
Manufacturer / Brand:	AMS
Guarantee:	2 years

### PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60

Connectors:



Top view:



In the kit:





DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60