

Code: ACAR-ECO-PLUS

## POWER DISTRIBUTION UNIT **ACAR-ECO-PLUS** (6 OUTLETS)

Net: **37.30 EUR** Gross: **45.88 EUR**

The new safety multi-outlet extension cord ACAR-ECO-PLUS enables save hundreds of kWh of electricity annually. Without any effort on your part, after switch off the main device (for example TV-set receiver connected to the "master" outlet) the ACAR-ECO-PLUS extension cord itself switch off the other devices connected to other outlets (for example: DVD player, Sat receiver, etc.), which can charge current in stand-by mode. It helps you to reduce electricity consumption in your home and environment protection.



### SPECIFICATION

Maximal load power:	2300 W
Nominal voltage:	230 V AC / 50 Hz
Fuse:	10 A / 250 V
Switch:	two-way
Leak current:	< 0.5 mA
Response time:	< 25 ns
Nominal voltage of surge suppressor:	250 V
Protection level:	1.3 kV (L/N)
Nominal stroke current:	2 kA (L/N) - (8/20 $\mu$ s)
Maximum stroke current:	6.5 kA (L/N) - (8/20 $\mu$ s)
Electric shock protection system:	Ground connectors (pins) connected with ground wire of AC mains
Housing:	Plastic - non-flammable
Number of output outlets:	<ul style="list-style-type: none"><li>• 1 MASTER outlet, two-contact with ground contact</li><li>• 3 SLAVE outlets with auto switch off the power supply after switch off the receiver powered from MASTER outlet</li><li>• 2 outlets separate from MASTER outlet</li></ul>
Length of the cable:	1.45 m
Dimensions:	447 x 55 x 53 mm
Weight:	0.56 kg
Guarantee:	2 years

### PRESENTATION

DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60

The extension cord has holders to arrange the cables:



## OUR OPINIONS



- Electricity saving perfect solution.
- The automatic fuse allows to continuous work of the device without any breaks due to device overloads or short-circuits.