

Code: ACAR-S8/FA/RACK

## POWER DISTRIBUTION UNIT **ACAR-S8/FA/RACK**

Net: **21.57 EUR** Gross: **26.53 EUR**

The surge suppressor reduces the risk of damage caused by surges in power lines to TV, radio, computer or other electronic equipment. The ACAR-S8/FA/RACK has the power switch with light indicator built-in, which inform about the power voltage in outlets. Fuses protect against any short-circuits and power surges. Power charge 10A.

It is equipped with black housing designed to mount in RACK 19" cabinets.



### SPECIFICATION

Rated voltage:	230 V AC / 50 Hz
Nominal load current:	10 A (total)
Nominal voltage of surge suppressor:	250 V / 50 Hz
Protection level of surge suppressor:	$\leq 1.3$ kV (L/N)
Number of outlets:	8 grounded outlets 10A/250V
Automatic delayed fuse:	✓
Nominal stroke current:	2 kA (L/N) - 8/20 $\mu$ s
Maximum stroke current:	6.5 kA (L/N) - 8/20 $\mu$ s
Leak current:	< 0.5 mA
Response time:	< 25 ns
Switch:	two-way, with light indication
Length of the cable:	2.9 m
Housing:	RACK 19", 1U, Plastic - non-flammable
Weight:	0.61 kg
Dimensions:	445 x 54 x 55 mm
Guarantee:	2 years

### PRESENTATION

Top view:



DELTA-OPTI Monika Matysiak; <https://www.delta.poznan.pl>  
POL; 60-713 Poznań; Graniczna 10  
e-mail: [delta-opti@delta.poznan.pl](mailto:delta-opti@delta.poznan.pl); tel: +(48) 61 864 69 60

In the kit:

