

Code: DH-PFM141

## AUDIO MODULE **DH-PFM141** DAHUA

The DH-PFM141 is designed to listen to sound from the surroundings and operate with DVRs. The device is equipped with microphone built-in inside aesthetic plastic housing, making it ideal for arranging practically at any room. It is perfect for suspended ceilings installations, because only part of the camera housing is visible for people. After installation it looks very aesthetic.



|                       |  |
|-----------------------|--|
| Bandwidth:            | 20 Hz ... 20 kHz   |
| Operation area:       | 5 m <sup>2</sup> ... 100 m <sup>2</sup>  |
| Power supply:         | 9 ... 15 V DC  |
| Current consumption:  | ≤ 100 mA, 60 mA (typical)  |
| Output impedance:     | 600 Ω  |
| Housing:              | Plastic  |
| Main features:        | <ul style="list-style-type: none"> <li>• SNR : 80 dB</li> <li>• Very good sensitivity of the microphone</li> <li>• Digital Noise Reduction</li> <li>• Auto Gain Control</li> <li>• Sensitivity adjustment</li> <li>• Dynamic range : 104 dB (1kHz @ max. 1dB SPL)</li> </ul> |
| Operation temp:       | -30 °C ... 70 °C   |
| Weight:               | 0.088 kg   |
| Dimensions:           | Ø 78 x 26 mm   |
| Manufacturer / Brand: | DAHUA  |
| Guarantee:            | <b>3 years</b>   |