

Code: DC-200

VOLTAGE CONVERTER **DC-200** 10 A

The DC-200 device converts the input voltage to the 12V DC value.



Type:	Decreasing the voltage, DC/DC
Power voltage:	21 V ... 30 V DC
Output voltage:	12 V ... 14 V DC
Output voltage adjustment:	—
Output current:	• 10 A (continuous operation) • max. 15 A (instantaneous operation)
Power:	• 120 W (continuous operation) • 200 W (instantaneous operation)
Protections:	• Overvoltage, • Undervoltage, • Short-circuit
Weight:	0.44 kg
Dimensions:	145 x 86 x 20 mm
Operation temp:	0 °C ... 40 °C
Guarantee:	2 years