

Code: REVEZ-HD-TRIO

## UNIVERSAL METER **REVEZ-HD-TRIO** DVB-T/T2, DVB-S/S2, DVB-C



The REVEZ-HD-TRIO allows to measure the TV signals at DVB-T/T2, DVB-S/S2, DVB-C installations. Readable menu will help the operation for any installer.

Output and input:	<ul style="list-style-type: none"> <li>• 2 pcs F socket</li> <li>• 1 pcs USB</li> <li>• 1 pcs HDMI output</li> </ul>
Frequency range:	950 MHz ... 2150 MHz - DVB-S / DVB-S2 174 MHz ... 858 MHz - DVB-T / DVB-C
Signal level:	<ul style="list-style-type: none"> <li>• - 65 ... - 25 dBm - DVB-S / DVB-S2,</li> <li>• - 85 ... - 20 dBm - DVB-T / DVB-C</li> </ul>
LNB power supply:	13 / 18 V - max. 400 mA
Antenna powering:	5 / 12 V
Switching between bandwidths:	0 / 22 kHz
DiSEqC:	DiSEqC 1.0, 1.1, 1.2 systems support
Modulation:	QPSK - DVB-S QPSK - DVB-S2 QPSK / 16-QAM / 64-QAM / 256-QAM - DVB-T 16, 64, 256 QAM - DVB-C
Video signal test:	✓
Programming and firmware upgrade:	via USB port



# DATA SHEET

Battery power supply:	<ul style="list-style-type: none"><li>• Li-Ion battery 11.4 V / 3000 mAh</li><li>• 15 V / 2000 mA (power adapter included)</li></ul>
Main features:	<ul style="list-style-type: none"><li>• Measurement of MER, SNR, Pre BER, Post BER, BER</li><li>• Satellite scanning function</li><li>• DisEqC automatic identification</li><li>• Constellation diagram</li><li>• Analysis of the spectrum for the whole frequency band</li><li>• Memory of 8000 channels</li><li>• The set includes a practical case</li><li>• High measurement accuracy</li><li>• Possibility to view TV channels</li><li>• Operation modes : PAL / NTSC</li></ul>
Weight:	0.556 kg
Dimensions:	168 x 105 x 44 mm
Supported languages:	English, Finnish, French, Greek, Spanish, German, Polish, Portuguese
Manufacturer / Brand:	REVEZ
Guarantee:	2 years