

Code: DHI-KB1000

RS-485 KEYBOARD CONTROLLER **DHI-KB1000** DAHUA

Analog keyboard with full possibilities of controlling and programming the PTZ camera heads of the DH-SD series, the Dahua recorders: analog, network, HD-CVI. It is also possible to control many DVRs from one keyboard.



Protocols:	AD1641M, ADMATRIX, BANKNOTE, CATU, DH-CC440, DH-MATRIX, DH-SD1, DH-SD2, EPTZ, GENERAL, HAIYU, HY, LILIN, MERCER, MERCER-1, PANASONIC, PE5051K, PELCO-9750, PELCOASCII, PELCOD, PELCOD-DON, PELCOD-S, PELCOD-S1, PELCOD1, PELCOP, PELCOP-A, PELCOP-HK, PELCOP1, PELCOP1-A, PELCOP5, PHILIPS, PIH-717, PELCOP-SD, QT-2XXD, RM110A, SAE, SAMSUNG, SANLI, SANTACHI, SHARP, SIERA-D, SIERA-P, SONY, WV-CS850I, WV-CS850II, WV-CS950, YAAN
Cameras numbers (ID):	1 ... 255
Maximal control distance:	1200 m
Communication standard:	<ul style="list-style-type: none"> • RS-485 - terminals • RS-422 - terminals
Manipulator:	3-axis joystick, Speed proportional to the swing (possibility of zoom control by joystick)
Display:	LCD - with light indication
PTZ control:	<ul style="list-style-type: none"> • Dahua or other manufacturers Speed Dome cameras • Recorders DAHUA
Power supply:	12 V DC / 1 A
Operation temp. / Relative humidity:	-10 °C ... 55 °C / max. 90 % - non-condensing
Weight:	0.65 kg
Dimensions:	330 x 160 x 105 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years