

Code: PCX/AM078-L0/PL

## ALARM CONTROL PANEL **PCX/AM078-L0/PL** PYRONIX

The PCX/AM078-L0/PL alarm control panel is intended for security of small and medium-sized facilities, offering comprehensive functionality in the field of security systems.



Mainboard inputs:	8 pcs
Mainboard outputs:	15 pcs
Maximal number of supported inputs:	78 pcs
Maximal number of supported outputs:	85 pcs
Users + admins:	100
Partitions:	—
Zones:	8
Events memory:	1250
Timers:	—
Supported keypads:	8 pcs ( 6 pcs wire )
Access from PC:	<ul style="list-style-type: none"> <li>• RS-232</li> <li>• PyronixCloud (PCX Insite application)</li> </ul>
Mobile phones support:	<ul style="list-style-type: none"> <li>• Android: Free application <a href="#">HomeControl+</a></li> <li>• iOS: Free application <a href="#">HomeControl+</a></li> <li>• Remote control of the control panel via SMS</li> </ul>



# DATA SHEET

Keyboard included:	—
Enclosure included:	✓
Protection class (Grade):	2
Power supply:	230 V AC
Operation temp:	-10 °C ... 40 °C
Weight:	5.3 kg (with enclosure and accessories)
Dimensions:	317 x 395 x 101 mm
Supported languages:	Polish
Manufacturer / Brand:	PYRONIX
SAP Code:	361301736
Guarantee:	2 years

