

Code: VERSA-LCDR-WH/IT

## KEYPAD FOR ALARM CONTROL PANEL **VERSA-LCDR-WH/IT** SATEL

The VERSA-LCDR-WH/IT keypad is intended for daily operations and programming the VERSA, VERSA Plus series alarm control system. With the LCD display showing text messages, even advanced functionalities of the alarm control unit are simple and convenient. The built-in proximity card reader allows to operate the system without the necessity to remember passwords.



Support:	VERSA, VERSA Plus
Main features:	<ul style="list-style-type: none"> <li>• Keypad backlight buttons</li> <li>• LEDs indicating device operation state</li> <li>• Quick switch on the selected standby mode by function keys</li> <li>• Alarms: keypad hold-down PANIC, FIRE and AUX</li> <li>• Buzzer for acoustic signaling of some system events</li> <li>• Panel communication loss indication</li> <li>• proximity reader built-in</li> <li>• Microswitch as tamper contact</li> <li>• Easy operation</li> </ul>
Power supply:	12 V DC
Current consumption:	max. 65 mA
Operation temp:	-10 °C ... 55 °C
Compliance with standards:	<ul style="list-style-type: none"> <li>• EN50130-5, Class II</li> <li>• EN 50131, Grade 2</li> </ul>
Weight:	0.24 kg
Dimensions:	139 x 124 x 22 mm
Manufacturer / Brand:	SATEL
Guarantee:	2 years