

Code: ASR2102A

FINGERPRINT READER + RFID **ASR2102A** DAHUA

Outdoor fingerprint reader with RFID reader built-in.



Cards support:	13.56 MHz S50
Reading distance of prox-keys:	0 ... 5 cm
Autonomous operation:	—
Keyboard built-in:	—
Doorbell button:	—
Tamper output:	✓
RS-485 interface:	✓
Communication:	RS-485
Power supply:	12 V DC
Maximal current consumption:	500 mA
Identification time:	≤ 1.5 s

Main features:	<ul style="list-style-type: none">• Memory of 3000 fingerprint patterns• Watchdog built-in• Buzzer• Operation status LED indicator• Opening by card or fingerprint and combination• Protections : Overvoltage, Overload
Operation temp:	-20 °C ... 65 °C
Permissible relative humidity:	5 ... 95 % (non-condensing)
"Index of Protection":	IP65 - after additional sealing the housing connection with the mounting surface, e.g. with silicone
Housing:	Plastic + Acrylic glass (plexiglass)
Color:	Silver / Black
Weight:	0.09 kg
Dimensions:	70 x 70 x 26 mm
Manufacturer / Brand:	DAHUA
Guarantee:	3 years