

Code: ARC3000H-FW2(868)

WIRELESS ALARM CONTROL PANEL **ARC3000H-FW2(868)** DAHUA

The ARC3000H-FW2(868) wireless alarm control panel supports max. 150 devices. In addition, the device allows you to handle max. 6 wireless sirens and up to 64 remote control keyfobs.



| | |
|--|---|
| Number of supported wireless detectors: | max. 150 pcs |
| Number of supported remote control keyfobs: | max. 64 pcs |
| The RFID cards/keyfobs support: | — |
| Number of supported wireless sirens: | max. 6 pcs |
| Operating frequency range of the wireless devices: | 868 MHz |
| Operating range in open area: | max. 2000 m |
| Keyboard included: | — |
| Expander included : | — |
| Built-in modules: | <ul style="list-style-type: none"> • LAN 10/100Mb • Wi-Fi 2.4 GHz / 5 GHz • GSM (GPRS, 3G, 4G LTE) - It supports push messages, SMS text notifications, and audio notifications via the phone |
| Access from PC: | <ul style="list-style-type: none"> • DMSS application - for the end user • COS Pro application - for the installer |
| Mobile phones support: | ✓ |
| Main features: | <ul style="list-style-type: none"> • Bidirectional communication • Two SIM cards support • Support for video events via a mobile client and email • Configuration via the www client, mobile client or software • LED indication |
| Power supply: | 12 V DC / 1.5 A (power adapter included) |
| Housing: | Plastic |
| Color: | White |



DATA SHEET

| | |
|-----------------------|-------------------|
| Operation temp: | -10 °C ... 55 °C |
| Weight: | 0.39 kg |
| Dimensions: | 163 x 163 x 32 mm |
| Manufacturer / Brand: | DAHUA |
| Guarantee: | 3 years |