

Code: HY-SA21A-W2(868)

WIRELESS SMOKE DETECTOR **HY-SA21A-W2(868)** DAHUA

Wireless smoke detector, which is designed to early detection of a developing fire. Besides sending the information to the control panel, the HY-SA21A-W2(868) detector can warn of the danger of using the built sound alarm.

The HY-SA21A-W2(868) supports the other devices compatible with wireless DAHUA system.



Support:	Wireless alarm systems DAHUA
Detection:	smoke
Alarm signaling:	<ul style="list-style-type: none"> • Buzzer ≥ 85 dB @ 3 m • LED indicator - red • Signal to control panel
Frequency band:	868 MHz
Radio communication range (at open area):	1000 m
Power supply:	1 x battery CR123A 3 V (included)
Backup time:	~ 3 years
Current consumption at standby mode:	≤ 35 μ A
Maximal current consumption:	≤ 35 mA

Main features:	<ul style="list-style-type: none">• Smoke detection - Chamber with photoelectric sensor• Frequency hopping against jamming for reliable transmission• Alarm mute function• Bidirectional communication• AES-128 data encryption• Ceiling mounting• Tamper detection - opening the enclosure
Color:	White
Operation temp:	-10 °C ... 55 °C
Weight:	0.13 kg
Dimensions:	Ø 98 x 43 mm
Manufacturer / Brand:	DAHUA
Guarantee:	2 years